# Quick Reference Sheet Cisco Unified IP Phone Model 7942G



# TELEPHONE FUNCTION

#### INTERNAL CAMPUS CALLS

- 1. Lift handset
- 2. Dial 4-digit extension for a campus line.
- 3. Converse

**Note:** You may also press **Speaker**, your extension button, *New Call* soft key, **Headset** button, Speed dial keys, Dial soft keys if using one of the directories, or the Redial soft key.

#### DIALING OFF-CAMPUS CALLS

- 1. Lift handset
- 2. Dial 8 + 1 + Area Code + 7-digit number for an outside line.
- 3. Converse

#### INTERNATIONAL DIALING

 8 + 011 + Country Code + City Code + 7digit Phone number + # + Access Code + #

#### ANSWER A CALL

- Lift handset
- If using a headset, press **Headset** button.
- To use speaker, press Answer soft key or **Speake**r button.

#### **END A CALL**

- Hang up handset
- Press **Headset** button if using a headset.
- Press *End Call* soft key
- If using Speaker, press **Speaker** button or *End Call* soft key.

#### **MUTING A CALL**

- Press **Mute** button, button will turn red.
- To disengage Mute, press **Mute** button and the red light will go off.

*Note:* Mute temporarily disables your microphone. Mute prevents the party from hearing you, but does not interfere with your ability to hear them.

#### PUTTING A CALL ON HOLD

- Press *Hold* soft key
- Press *Resume* soft key to return to call on hold.

#### TRANSFER A CALL

- 1. When ready to transfer a call, press *Transfer* soft key.
- 2. Dial 4-digit extension to transfer to.
- 3. When line rings and party answers, press *Transfer* soft key again to complete the transfer.

#### TRANSFER A CALL TO VOICEMAIL

- 1. When ready to transfer a call, press *Transfer* soft key.
- 2. Dial \* plus the 4-digit extension to transfer to. (ex: \*6400)
- 3. Press the *Transfer* soft key again to complete the transfer.

#### CALL FORWARD ALL CALLS

- 1. Press CfwdAll soft key
- 2. Enter the extension for where your calls will forward to: 4-digits for on-campus, or 8+1+10-digits for off-campus
- To CANCEL a forward: press *CfwdAll* soft key.
- You can also update this in the <u>Self Care Portal</u> *Note:* If forwarding to voicemail, press *CfwdAll* soft key, then your **Messages** button.

#### LAST NUMBER REDIAL

• Press Redial soft key

#### **CONFERENCE CALL**

- 1. During a call, press *More* soft key, then press *Confrn* soft key.
- 2. You will get dial tone, so you can dial an additional party.
- 3. Press Confrn again to add new party.
- Repeat to add more

#### **IDIVERT**

- 1. Call rings on your phone
- 2. Press *iDivert* soft key during ringing.
- 3. Call then forwards directly to your voice mailbox.

# Quick Reference Sheet Cisco Unified IP Phone Model 7942G



# **UNITY VOICEMAIL**

Please note: messages are only retained in the inbox for 2 weeks. A permanent archive of all voicemails is available in the email notification sent to your UA address.

#### ACCESSING VOICEMAIL

\*\*Your default PIN is: 135790#

## Logging into voicemail from your phone:

- 1. Press *Message* button
- 2. Enter your PIN followed by #.
- 3. Follow prompts to setup your mailbox.

## Calling voice mailfrom outside the system:

- 1. Dial 907-796-5555
- 2. Once the system answers, press \*
- 3. The system will then ask you for your ID number. Your ID is your 10-digit dialing number followed by #.
- 4. Then you will enter your password, followed by #.

#### MAIN MENU PROMPTS

- 0 Help
- \* Cancel/back up
- # Skip/Move Ahead
- 1 Play New Messages
- 2 Send Messages to other extensions on this voicemail system.
- 3 Check Saved Messages
- 4 Change Set Up Options

# UAS EMERGENCY ALERT SYSTEM

See instructions on the Health & Safety website

#### **DURING A MESSAGE YOU MAY PRESS:**

- 1 = Repeat
- 2 = Save
- 3 = Delete
- 4 = Slower
- 5 = Change Volume
- 6 = Faster
- 7 =Rewind 3sec
- 8 = Pause/Resume
- 9 = Fast Forward
- # = Fast Forward to end of message
- ## = Save as New

#### **AFTER LISTENING TO A MESSAGE:**

- 1 = Repeat
- 2 = Save
- 3 = Delete
- 4 = Reply
- 5 = Forward
- 6 = Mark as New
- 7 = Skip Back
- 9 = Play message properties

## Voicemail access via website:

- 1. Go to Cisco Web Inbox
- 2. Log in with your UA credentials
- 3. Select a voicemail
- 4. Click the Play button ( )

#### You can also:

- Click the Forward button to send this message as an email to another inbox
- Click the Delete button to remove the message